

IC CROSS REFERENCE: 10BASE-T MODULES

IC Manufacturer	IC Part No.	Sumlink Part No.	Ports Supported	Configuration		Turns Ratio		Package		
				TX	RX	TX	RX	Style	L/W/H(in)	
AMD	AM79C90, AM79C98, AM79C100,AM79C940 AM79C960,AM79C961, AM79C965,AM79C970, AM79C971,AM79C981, AM79C982,AM79C983, AM79C961(PC net-ISA II)	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280	
		ST-85433	Single Port	F,T,C	F,T	1CT:1CT	1CT:1CT	DIL	.800/.400/.250	
		ST-J1101	Single	T,C	T,C	1CT:2.5	1CT:1	1X1 ICM	.850/.630/.535	
		AM79C984,AM79C985, AM79C988,AM79C989	ST-88049	Quad Port	T,C	T	1CT:1CT	1:1	SMT	1.125/.640/.230
		ST-88050	Quad Port	T	T	1CT:1CT	1:1	SMT	1.125/.640/.230	
		ST-F5017	Single Port	T,C	T	1CT:1CT	1CT:1CT	SMT	.450/.360/.220	
		AM186CC15DN	ST-J1101	Single	T,C	T,C	1CT:2.5	1CT:1	1X1 ICM	.850/.630/.535
	Cirrus Logic	CS8900,CS8920	ST-88062	Quad Port	T,C	T	1CT:1.414CT	1:1	SMT	1.125/.640/.230
			ST-88065	Quad Port	T	T	1CT:1.414CT	1:1	SMT	1.125/.640/.230
			ST-356SM	Single Port	T,C	T,C	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220
ST-85745			Single Port	T	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-J1101	Single	T,C	T,C	1CT:2.5	1CT:1	1X1 ICM	.850/.630/.535	
CS8900A-CQ3		ST-F2023	Single Port	T,C	T,C	1CT:2.5CT	1CT:1CT	SMT	.450/.360/.220	
		ST-J1101	Single	T,C	T,C	1CT:2.5	1CT:1	1X1 ICM	.850/.630/.535	
	CS8900A-RQ3	ST-F2024	Single Port	T,C	T,C	1CT:2.5CT	1CT:1CT	SMT	.450/.360/.220	
Davicom	DM9008,DM9009	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280	
	DM9081,DM9095	ST-85433	Single Port	F,T,C	F,T	1CT:1CT	1CT:1CT	DIL	.800/.400/.250	
Fujitsu	MB86967	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280	
	MB86951,MB86961, MB86964,MB86965B	ST-356SM	Single Port	T,C	T,C	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-88048	Single Port	T,C	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-85745	Single Port	T	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
Intel (Level One)	LXT901A,LXT907A	ST-356SM	Single Port	T,C	T,C	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-88048	Single Port	T,C	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-85745	Single Port	T	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
	LXT905,LXT908	ST-467SM	Single Port	T,C	T,C	1CT:2CT	1CT:1CT	SMT	.450/.360/.220	
		LXT902	ST-88026 ST-85433	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280
	Single Port	F,T,C		F,T	1CT:1CT	1CT:1CT	DIL	.800/.400/.250		
	LXT914,LXT915,LXT916 LXT917,LXT918,LXT944	ST-88062	Quad Port	T,C	T	1CT:1.414CT	1:1	SMT	1.125/.640/.230	
		ST-88065	Quad Port	T	T	1CT:1.414CT	1:1	SMT	1.125/.640/.230	
	LSI	L64381	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280
		80C24	ST-85433	Single Port	F,T,C	F,T	1CT:1CT	1CT:1CT	DIL	.800/.400/.250
Lucent	T7213, T7241A	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280	
		ST-85433	Single Port	F,T,C	F,T	1CT:1CT	1CT:1CT	DIL	.800/.400/.250	
Microlinear	ML2652,ML2653 ML4652,ML4658	ST-435SM	Single Port	T	T	2CT:1CT	1CT:1CT	SMT	.450/.360/.220	
	Motorola	MC68610	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280
		ST-85433	Single Port	F,T,C	F,T	1CT:1CT	1CT:1CT	DIL	.800/.400/.250	
National Semiconductor	DP83901A	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280	
	DP83902A,DP83902	ST-85433	Single Port	F,T,C	F,T	1CT:1CT	1CT:1CT	DIL	.800/.400/.250	
	DP83905,DP83934									
Realtek	RTL8301	ST-88049	Quad Port	T,C	T	1CT:1CT	1:1	SMT	1.125/.640/.230	
	RTL8019AS	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280	
	RTL8029AS	ST-88026	Single Port	F,T,C	F,T,C	1CT:1CT	1CT:1CT	SMT	1.000/.500/.280	
Texas Instruments	TNETE100A	ST-356SM	Single Port	T,C	T,C	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-88048	Single Port	T,C	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-85745	Single Port	T	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
	TNETE2004	ST-88062	Quad Port	T,C	T	1CT:1.414CT	1:1	SMT	1.125/.640/.230	
		ST-88065	Quad Port	T	T	1CT:1.414CT	1:1	SMT	1.125/.640/.230	
		ST-356SM	Single Port	T,C	T,C	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-88048	Single Port	T,C	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		ST-85745	Single Port	T	T	1CT:1.414CT	1CT:1CT	SMT	.450/.360/.220	
		TNETE2008	ST-88049	Quad Port	T,C	T	1CT:1CT	1:1	SMT	1.125/.640/.230

Configuration: T= Transformer, F= Low Pass Filter, C= Choke

Package Styles: DIL- Dual-In-Line package, SMT- Surface Mount Package